

AUTO CHARGE[®] 12 DV

SINGLE SYSTEM BATTERY CHARGER SINGLE SYSTEM BATTERY CHARGER



MODEL # 091-165-12-DV

Ideally suited for vehicles used in localities, which may have only 230 volts, this charger has an input voltage selector switch. The Auto Charge 12 DV is a fully automatic battery charger for vehicles with a single battery. Unique electronic sensing circuits sense the true battery voltage while eliminating the need for external sense wires. The maximum output of the charger is 12 amperes. When the battery is fully charged, all charging stops. There is no overcharging and no water boil off. It is ruggedly constructed for mounting in the vehicle.

This charger has two indicator options: Option 1 is a Bar Graph battery condition display. Option 2 is a low cost LED Indicator, that shows when the charger is "ON" and when it is "CHARGING."

SPECIFICATIONS:

Input: 115 / 230 Vac, 50/60 Hz, 3 / 1.5 Amps Max

Input Fuse: 5 Amps, Fast Acting

Output: 12 Vdc, 12 Amps

Output Fuse (Recommended): 24 Amps

Charge Indicator: 0-15 Amps

Weight: 12 lbs

Warranty: 3 Years



ENERGIZED AND READY, WHEN SECONDS COUNT

12 AMPS FOR CHARGING VEHICLE BATTERIES

AUTOMATICALLY CHARGES BATTERY

INPUT VOLTAGE SELECTABLE, 115 VOLTS OR 230 VOLTS

DESIGNED SPECIFICALLY FOR VEHICLES WITH SINGLE BATTERY SYSTEMS

AMMETER INDICATES CHARGE RATE

NO WATER BOIL OFF

3 YEAR WARRANTY

OPTIONAL INDICATORS

BAR GRAPH DISPLAY



Model 091-165-016


10 Element, Weatherproof Single Bar Graph battery condition display.

LOW COST LED INDICATOR



Model 091-11-102-12

LED Indicator shows when the charger is "ON" and when it is "CHARGING".



091-165-12-DV Outline Drawing